

PICO PROTECTOR® PG-25 & PK-25 Series

Installation Instructions



LISTED 95P5 SIGNAL CIRCUIT PROTECTOR

Introduction

The Siemon Company's Pico Protector® Kits protect voice and data equipment from sneak current and voltage surge conditions that may occur beyond primary protection devices. Such conditions may cause fire, electrical shock, and damage to customer premises equipment (CPE). This secondary line protection is installed behind the network interface device (NID) and used in conjunction with primary protection devices (when required).

Both the PG and PK series kits follow the same installation instruction procedure. For proper protection, a ground cable must be connected to the kit's terminal-plate assembly.




Figure A

Safety Considerations


For UL 497A compliance the PICO Protector® is installed in a UL listed type 1 enclosure with UL listed Siemon Company S66M series connecting blocks. The installation, including earth ground connection, is to be made in accordance with National Electric Code requirements and local authorities. Connecting blocks may be purchased separately or in kit form with grounding hardware.

Pico Protector ground kits and protector modules are purchased separately.

Protectors must be installed and maintained by trained service personnel only.

WARNING:

This product may only be installed on the protected side of the primary building entrance protector (when present). These instruction procedures must be followed explicitly to avoid safety hazards to equipment, plant and personnel.



**Figure B
(Pico Circuit)**

Ground kits for 25-pair protection

P/N: PG-25 & PK-25

General:

The PG-25 kit is used on 66M blocks loaded with at least two rows of electrically isolated quick clips. It may be added to blocks that are already installed or used on new installations. The PK-25 series kits consist of a PG-25 ground kit and a connecting block of the user's choice. Consult factory to determine block best suited to meet specific applications.

PG-25 Kit includes:

- One bus bar assembly
- One terminal-support assembly plate with snap-on mounting ears
- Two 4-inch female-ended quick-connect jumpers

1. Mount Block:

For proper installation, quick clips in rows A or B must be wired to the network interface or primary protection. Rows C or D must be wired to premises equipment. If bridging clips are in place, they must be selectively removed prior to module installation.

2. Attach bus bar to block:

Align the bus bar above the fanning strip on the side of the block wired to the NID. Bus bar contacts should face center of the block. Snap bus bar onto fanning strip using the inside mounting position. See Figure C.




Figure C

3. Mount terminal-support assembly:

Snap terminal-support assembly onto the central portion of the block's NID side fanning strip. See Figure D.

4. Connect ground wire:

Connect #6 ground wire (not included) to terminal-support assembly by sliding the ground wire into the box lug on the plate and tightening the screw (slotted screw driver required). See Figure D.




Figure D

5. Attach grounding jumper wires:

Connect one end of each jumper wire to a quick-connect tab on the terminal support assembly and the other end of each jumper wire to a quick-connect terminal on the bus bar assembly. See Figure E. **The bus bar assembly is not properly grounded until both jumper wires are installed.**

6. Mount modules

Push modules onto quick clip rows B and C of the block such that the ground tab on each module mates with one of the 25 bus bar contacts. See Figure E.




Figure E

7. Circuit designations

Write circuit designations on grounding-tab shroud of module. Slide optional red designation caps onto the handle to designate priority circuits. See Figure F.

Pico Protector[®] Trouble Guide

Follow steps 1 - 3 if signal lost at the workstation outlet:

1. Disconnect all premises equipment and test (using TP-4P, see Figure G) for tone on CPE side of the Pico Module (side opposite ground tab).
 - a. If tone registers, the trouble is between the outlet and the secondary protector block. Trace the line back to the workstation outlet to identify and repair.
 - b. If tone does not register, proceed to step 2.




Figure F

2. Test for tone on the NID side of the Pico Module (same side as ground tab).
 - a. Tone registering on NID side but not on CPE side indicates a blown fuse(s). Remove module and replace spent fuse(s) using a 1/16" diameter probe (TP-4P). Fully seated fuses are recessed in housing approximately 0.10 inch. Re-install the module and test.
 - b. No tone on both the NID and CPE sides of the installation Pico Module indicates either a case of trouble on the incoming line or a transistor malfunction in the module (provided that all premises equipment is disconnected). See caution and proceed to step 3.
3. Remove the module and test the quick clips wired to the NID.
 - a. If tone registers, the transistor in the module has failed short to ground due to a catastrophic voltage surge. Discard the old module and replace it with a new one of the same part number. Retest.
 - b. If no tone registers, the trouble is with the incoming line. Reinsert the module and test the circuit at the building entrance point (NID) or primary protection to isolate the trouble.

continued page 10

Caution:

If no tone exists on both the CPE and NID sides of the module and one or more of the fuses are blown, a sustained voltage surge condition may exist that is below the breakdown voltage of the primary protector. For this case, care must be taken by service personnel to avoid electrical shock until the line is checked and treated for the presence of an extraneous voltage source.

Warranty

The Siemon Company (Seller) warrants to the purchaser that its Pico Protector® (Product) will be free from defects in materials and workmanship. Seller, at its election, will repair, replace or refund the purchase price for any Product proven to be defective within one year of date of purchase which has not been altered or repaired by one other than Seller and which has not been improperly installed or improperly used. Any action with respect to this warranty must be brought within one year of date of purchase. ***This warranty is in lieu of all other warranties, expressed or implied, and all other warranties, including but not limited to, warranties as to merchantability and fitness for a particular purpose are expressly disclaimed.*** Seller will not be liable for any general, special, or consequential damages, whether arising in contract, tort or strict liability, and in no event will Seller be liable for any damages in excess of the purchase price of the Product.




Figure G

Accessory Information

P/N	Description	Std. Pck.
CP-675-C	Red designation caps	100/bag
TP-4P	4-point test probe	10/box
SF-035	Replacement fuses	20/bag

Modules:

P/N	Clamping Level \pm 10%	Std. Pck.
PM-007	7V	100/ctn.*
PM-027	27V	100/ctn.*
PM-068	68V	100/ctn.*
PM-140	140V	100/ctn.*
PM-180	180V	100/ctn.*
PM-230S	255V	100/ctn.*

*packed 25 per box

The Americas

Watertown, CT USA
Phone (1) 860 945 4200

Europe/Middle East/Africa

Surrey, England
Phone (44) 0 1932 571771

Asia/Pacific

Shanghai, P.R. China
Phone (86) 21 6390 6778

Japan

Tokyo, Japan
Phone (03) 5437 1580



SIEMON™

www.siemon.com

Rev. B 06/06 100.0765

© 2006 Siemon